

# Compatibility of power tubes with OCTAVE integrated amplifiers and power amplifiers

## Current models

Date: 06/2021

Model	6L6	EL34 / KT77	6550	KT88	KT120	KT150	KT170	300 B	300B XL	Serial Tube Set
Models without a power selector switch										
V 16	-	-	+	+	+	+	-	-	-	KT120
V 40 SE	+	+	+	+	-	-	-	-	-	6550
V 70 SE	-	+	+	+	+	-	-	-	-	6550
Jubilee Mono SE	-	-	-	+	+	+	-	-	-	KT120
Models with power selector switch										
V 70 Class A	-	-	+LOW	+LOW	+HIGH	+HIGH	-	-	-	KT120
V 80 SE	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	-	-	-	KT150
V 110 SE	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	-	-	-	KT120
RE 320	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	+HIGH	-	-	KT150
MRE 220	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	+HIGH	-	-	KT120
Jubilee 300 B	-	-	-	-	-	-	-	+MED	+HIGH	300 B

<b>+</b>	Can be used
<b>+LOW</b>	Can be used if the power selector is set to "LOW"
<b>+MED</b>	Can be used if the power selector is set to "MED"
<b>+HIGH</b>	Can be used if the power selector is set to "HIGH"
<b>-</b>	Must not be used

## Compatibility of power tubes with OCTAVE integrated amplifiers and power amplifiers

### Discontinued models

Date: 06/2021

Ausgelaufene Modelle	6L6	EL34 / KT77	6550	KT88	KT120	KT150	KT170	Serial Tube Set
Models without a power selector switch								
V 40	+	+	+	+	-	-	-	EL34
V 50 (MK2)	+	+	+	+	-	-	-	EL34
V 70	-	+	+	+	+	-	-	6550
V 80	-	+	+	+	+	+	+	6550
RE 280 (MK2)	-	+	+	+	+	-	-	6550
MRE 120	-	+	+	+	+	-	-	6550/KT88
MRE 130	-	+	+	+	+	+	+	6550
Jubilee Mono	-	-	+	+	+	+	-	6550
Models with power selector switch								
V 110	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	-	KT120
RE 290	-	+LOW	+LOW	+LOW	+HIGH	+HIGH	+HIGH	KT120

+	Can be used
+LOW	Can be used if the power selector is set to "LOW"
+HIGH	Can be used if the power selector is set to "HIGH"
-	Must not be used